

Deskpro 1000

System Boards	Spare Part
System Board (P55C)	333814-001

Config. Jumpers, Pentium			
Jumper	Function	Setting	Description
CPW*	Clear CMOS	1-2	Clear, remove after 60 seconds

* Jumper is installed on one pin of header.

CPU BUS Frequency Settings			
BUS Proc. Speed (MHz)	CLK1	CLK2	CLK3
66 MHz*	1-2	1-2	1-2
60 MHz	2-3	1-2	1-2
55 MHz	2-3	2-3	1-2

* Default setting.

CPU Speed Settings			
BUS Proc. Speed (MHz)	FREQ1	FREQ2	FREQ3
233 MHz	1-2	1-2	1-2
200 MHz	1-2	2-3	1-2
166 MHz*	2-3	2-3	1-2

* Default setting.

Configuration Code	System Board Spare Part
BWF2	333814-001

Microprocessors	Spare Part
P5/200 (P55C) w/ Thermal Pad	240181-002

Memory	Spare Part	System
8 MB SIMM, 60ns, EDO	285734-001	P55C
16 MB SIMM, 60ns, SDRAM	333820-001	P55C

Miscellaneous	Spare Part	System
Mouse, Opal	298792-001	DT (P54C)

Controller Boards	Spare Part	System
Video Board	333821-001	P55C
Video Memory, 512KB	333822-001	P55C

Hard Drives	Spare Part	System
2.1 GB, IDE	333816-001	P55C

Diskette Drives	Spare Part	System
1.44 MB, 3-Mode	333817-001	All

Cables	Spare Part	System
Cable Kit (floppy, hard drive, hard drive/power LED cables)	333824-001	All

Power Supply/Battery	Spare Part	System
Power Supply	333818-001	P55C
Lithium Battery, CR2032	234556-001	P55C

Deskpro 1000

MEMORY UPGRADE CHART

No Compaq memory options are supported. Use Service Advisory A1715 to upgrade.