

Deskpro 450

System Boards	Assembly	Spare Part	System
System Board, AM ³ , PCI, 8 MB, ENET, w/o Processor	003904-101	172168-001	3x3 ¹ , 4x4 ²
System Board, AM, PCI, 8 MB, w/o Processor	003907-101	172169-001	3x3, 4x4
System Board, AM, PCI, ENET, 8 MB, w/o Processor	003786-101	173146-001	3x3, 4x4

¹ 3x3 = 3 bay, 3 slot form factor. ² 4x4 = 4 bay, 4 slot form factor.

³ AM = Asset Management.

Configuration Jumpers, 486-Based System Boards (003786, 003904, 003907)

Jumper	Function	Setting	Description
E5	Internal/External Battery	1 – 2	Internal (on-board) Battery
		2 – 3	External Battery. Connect at header P3.
E6	Password Enable/Disable	1 – 2	Password Enabled
		2 – 3	Password Disabled

SW1, Speed Settings, 486-Based System Boards (003786, 003904, 003907)

CPU Type/Operation	S1	S2	S3	S4
486DX2/50	ON	ON	OFF	OFF
486DX2/66	ON	OFF	OFF	OFF
486DX4/100	ON	OFF	OFF	OFF

Configuration Code *	Assembly	System Board Spare Part	Form Factor
HKR1**	003904-101	172168-001	3x3
HKR1**	003786-101	173146-001	3x3
HKR2**	003904-101	172168-001	3x3
HKR2**	003786-101	173146-001	3x3
HKR3	003907-101	172169-001	3x3
GKR2**	003904-101	172168-001	3x3
GKR2**	003786-101	173146-001	3x3
GKR3	003907-101	172169-001	3x3
HKT1**	003904-101	172168-001	4x4
HKT1**	003786-101	173146-001	4x4
HKT2**	003904-101	172168-001	4x4
HKT2**	003786-101	173146-001	4x4
HKT3	003907-101	172169-001	4x4
GKT2**	003904-101	172168-001	4x4
GKT2**	003786-101	173146-001	4x4
GKT3	003907-101	172169-001	4x4

* "G" codes are European models. "H" codes are worldwide.

** Must use assembly number AND configuration code to order spare.

Microprocessors	Spare Part	System
486DX2/50	172937-001	3x3, 4x4

Deskpro 450

Memory	Assembly	Spare Part	System
4 MB SIMM, 70ns	172707-002	172718-001	3x3, 4x4
8 MB SIMM, 70ns	172707-003	172719-001	3x3, 4x4
16 MB SIMM, 70ns	172707-004	172938-001	3x3, 4x4
32 MB SIMM, 70ns	172707-005	172939-001	3x3, 4x4
128K Cache Memory	003868-001	172085-001	3x3, 4x4
256K Cache Memory	004416-001	172894-001	3x3, 4x4
1 MB Video Memory, DRAM ¹	004120-001	171044-001	3x3, 4x4
1 MB Video Memory, VRAM ²	003971-001	172467-001	3x3, 4x4

¹ Cirrus Logic GD 5434.

² Qvision 1280P+.

Miscellaneous	Assembly	Spare Part	System
Backplane	003730-001	172622-001	3x3
Backplane	003733-001	172623-001	4x4
Speaker w/o Bracket	141045-001	141336-001	3X3, 4X4
WSS Feature Card	004198-001	172078-001	4X4

Controller Boards	Assembly	Spare Part	System
6260 SCSI-2 Controller*	004004-001	133880-001	3x3, 4x4
Ethernet ISA Controller w/ Slot Bracket	003086-001	147220-001	3x3, 4x4
IDE Controller	002172-001	171745-001	3x3, 4x4
SCSI, ISA, Plug and Play	184750-001	184751-001	3x3, 4x4, 5x5
Token Ring Controller w/ Cable & Bracket		172194-001	3x3, 4x4
Token Ring Controller w/o Cable & Bracket		172885-001	3x3, 4x4

* See Multiproduct Boards Appendix for settings.

Hard Drives	Type	Spare Part	System
270 MB, IDE, DFP*	65/66	172778-001	3x3, 4x4
420 MB, IDE	65	172780-001	3x3, 4x4
535 MB SCSI	N/A	148286-001	3x3, 4x4
540 MB, DFP	65	188666-001	3x3, 4x4
1.08 GB, IDE, DFP	65	172941-001	3x3, 4x4
1.05 GB SCSI	N/A	192799-001	3x3, 4x4
2.1 GB fast SCSI-2	N/A	142272-001	3x3, 4x4

* DFP = Drive Fault Prediction.

Tape Drives	Spare Part	System	Tape Cartridge	Spare Part
340/680 MB with Compression	187658-001	3x3, 4x4	340 MB 680 MB	184299-001 184300-001
525 MB ACA	142073-201	3x3, 4x4	525 MB	119504-001
4 GB TR4, IDE	294126-001		4 GB TR4	294140-001
5.0 GB DAT	142074-201	3x3, 4x4	2.0 GB DAT 5.0 GB DDS2	131148-001 199496-001

CD-ROM Drive	Spare Part	System
CD-ROM, Internal, QuadSpeed, IDE	172717-001	3x3, 4x4
CD-ROM, 16X, IDE, Slot Load, 5.25", Half Height	278791-001	All

Deskpro 450

Diskette Drives	Spare Part	System
1.44 MB, 3-Mode	160788-201	3x3, 4x4

SpeedPac 144/I Internal Fax/Modem

Country	Assembly	Spare Part	System
U.S.*	003002-001	147453-001	3x3, 4x4

* See Modem Configuration Appendix for settings.

28.8k-bps Modem

Country	Assembly	Spare Part	RJ-11 Phone Cable
U.S.	223610-002	259214-002	127949-001

Cables	Spare Part	System
2-Device SCSI, 3-Connector	146997-001	3x3, 4x4
2-Device SCSI, 3-Connector, Plug and Play	184118-001	3x3, 4x4
Adapter, AUI to BNC E/Net Transceiver, External	192768-001	3x3, 4x4
Diskette Drive Cable (3x3)	172477-001	3x3
Diskette Drive Cable (4x4)	172797-001	4x4
Hard Drive Select Cable	172945-001	3x3, 4x4
Kit: IDE CD-ROM/HD Cable (2); Audio Cable (2)	172478-001	3x3, 4x4
LED Cable Assembly	172531-001	3x3, 4x4
Monitor ID Cable (asset control)	172482-001	3x3, 4x4
Token Ring Cable	172844-001	3x3, 4x4


ROM Information	Spare Part	System
System ROMPac	148218-001	3x3, 4x4

Battery/Power Supply	Spare Part	System
Battery Clock, Real-Time (4.5 V Alkaline)	160274-001	3x3, 4x4, 5x5
Power Supply, 145 W, US	172765-001	3x3, 4x4
Power Supply, 145 W, PFC, Outside US	172766-001	3x3, 4x4


Deskpro 450

Memory Upgrade Chart

PROCESSOR BOARD
003786/003904/003907
(8 MB)



ADD ANY COMBINATION OF THE FOLLOWING MEMORY MODULES,
UP TO 136 MEGABYTES TOTAL SYSTEM MEMORY



4-MB 70ns - OPTION PN 172712-001

8-MB 70ns - OPTION PN 172713-001

16-MB 70ns - OPTION PN 172714-001

32-MB 70ns - OPTION PN 172715-001